

LEDR[0]	PIN_R20	HEX0[0]	PIN_J2	KEY[0]	PIN_R22
LEDR[1]	PIN_R19	HEX0[1]	PIN_J1	KEY[1]	PIN_R21
LEDR[2]	PIN_U19	HEX0[2]	PIN_H2	KEY[2]	PIN_T22
LEDR[3]	PIN_Y19	HEX0[3]	PIN_H1	KEY[3]	PIN_T21
LEDR[4]	PIN_T18	HEX0[4]	PIN_F2		
LEDR[5]	PIN_V19	HEX0[5]	PIN_F1		
LEDR[6]	PIN_Y18	HEX0[6]	PIN_E2	CLOCK_27	PIN_D12
LEDR[7]	PIN_U18			CLOCK_50	PIN_L1
LEDR[8]	PIN_R18			CLOCK_24	PIN_B12
LEDR[9]	PIN_R17	HEX1[0]	PIN_E1	EXT_CLOCK	PIN_M21
		HEX1[1]	PIN_H6		
		HEX1[2]	PIN_H5		
LEDG[0]	PIN_U22	HEX1[3]	PIN_H4		
LEDG[1]	PIN_U21	HEX1[4]	PIN_G3		
LEDG[2]	PIN_V22	HEX1[5]	PIN_D2		
LEDG[3]	PIN_V21	HEX1[6]	PIN_D1		
LEDG[4]	PIN_W22				
LEDG[5]	PIN_W21				
LEDG[6]	PIN_Y22	HEX2[0]	PIN_G5		
LEDG[7]	PIN_Y21	HEX2[1]	PIN_G6		
		HEX2[2]	PIN_C2		
		HEX2[3]	PIN_C1		
SW[0]	PIN_L22	HEX2[4]	PIN_E3		
SW[1]	PIN_L21	HEX2[5]	PIN_E4		
SW[2]	PIN_M22	HEX2[6]	PIN_D3		
SW[3]	PIN_V12				
SW[4]	PIN_W12				
SW[5]	PIN_U12	HEX3[0]	PIN_F4		
SW[6]	PIN_U11	HEX3[1]	PIN_D5		
SW[7]	PIN_M2	HEX3[2]	PIN_D6		
SW[8]	PIN_M1	HEX3[3]	PIN_J4		
SW[9]	PIN_L2	HEX3[4]	PIN_L8		
		HEX3[5]	PIN_F3		
		HEX3[6]	PIN_D4		

JP1 - GPIO 0

IO_A0	Pin_A13	1	2	Pin_B13	IO_A1
IO_A2	Pin_A14	3	4	Pin_B14	IO_A3
IO_A4	Pin_A15	5	6	Pin_B15	IO_A5
IO_A6	Pin_A16	7	8	Pin_B16	IO_A7
IO_A8	Pin_A17	9	10	Pin_B17	IO_A9
Vcc 5		11	12	Gnd	
IO_A10	Pin_A18	13	14	Pin_B18	IO_A11
IO_A12	Pin_A19	15	16	Pin_B19	IO_A13
IO_A14	Pin_A20	17	18	Pin_B20	IO_A15
IO_A16	Pin_C21	19	20	Pin_C22	IO_A17
IO_A18	Pin_D21	21	22	Pin_D22	IO_A19
IO_A20	Pin_E21	23	24	Pin_E22	IO_A21
IO_A22	Pin_F21	25	26	Pin_F22	IO_A23
IO_A24	Pin_G21	27	28	Pin_G22	IO_A25
Vcc 33		29	30	Gnd	
IO_A26	Pin_J21	31	32	Pin_J22	IO_A27
IO_A28	Pin_K21	33	34	Pin_K22	IO_A29
IO_A30	Pin_J19	35	36	Pin_J20	IO_A31
IO_A32	Pin_J18	37	38	Pin_K20	IO_A33
IO_A34	Pin_L19	39	40	Pin_L18	IO_A35